

Profile Name	Example	Description	Applicable Sensors/Zones	Entry/Exit Delay	Active in Arm Stay	Active in Arm Away	Active in Disarm	Follower	Alarm Type	Siren Type	Require Restoral	Report Code	Tamper Alarm Active	Delay Alarm Report
24 Hour	24-Hour zone is most often used with life-safety devices like smoke detectors, carbon monoxide detectors, panic buttons and medical alert buttons. It may also be used for doors that should not be opened under normal circumstances, such as emergency exits, fire doors, or gun safes.	Special Intrusion, active in disarm, 24 hour	D/W, Wired Input Module, D/W with Contact	Disabled	Yes	Yes	Yes	Disabled	Auxiliary	Intrusion	Yes	133	Yes	Yes
Auxiliary (Medical)	Used to trigger and auxiliary (medical) alarm to Central Station and emits a low volume siren on ClareOne	Auxiliary, Medical panic	Panic Sensor, Wired Input Module, D/W with Contact	Disabled	Yes	Yes	Yes	Disabled	Aux	Low Level	Yes	150	Yes	Yes
Auxiliary Silent (Medical)	Used to trigger and auxiliary (medical) alarm to Central Station with a no siren on ClareOne	Auxiliary, Medical panic	Panic Sensor, Wired Input Module, D/W with Contact	Disabled	Yes	Yes	Yes	Disabled	Silent Auxiliary	None	Yes	150	Yes	Yes
CO	A 24 hour zone for Carbon Monoxide life safety devices. Should not be used for any device that is not a CO sensor. When tripped an alarm is sent to the Central Station regardless of the arming status of ClareOne.	Carbon Monoxide	Carbon Monoxide, Wired Input Module	Disabled	Yes	Yes	Yes	Disabled	Carbon Monoxide	T4	Yes	162	No	No
Entry/Exit Long	For security zones which are associated with entry and exit points on the premises, uses the long exit delay by default.	Intrusion, Perimeter, with long delay	D/W, Wired Input Module, D/W with Contact	Long	Yes	Yes	No	Disabled	Intrusion	Intrusion	Yes	134	Yes	Yes
Entry/Exit Standard	For security zones which are associated with entry and exit points on the premises, uses the standard exit delay by default.	Intrusion, Perimeter, with standard delay	D/W, Wired Input Module, D/W with Contact	Standard	Yes	Yes	No	Disabled	Intrusion	Intrusion	Yes	134	Yes	Yes
Fire	For smoke and fire detection devices. When tripped an alarm is sent to the Central Station regardless of the arming status of ClareOne.	Fire, smoke sensor	Smoke, Wired Input Module Zone	Disabled	Yes	Yes	Yes	Disabled	Fire	T3	Yes	110	No	No
Fire Panic	Any device that when tripped will initiate a fire panic alarm. Might be used on exit doors that are to be opened only in case of fire or on a pull station.	Fire Panic	Keypad, Wired/Wireless Pull Station, Wired Input Module Zone	Disabled	Yes	Yes	Yes	Disabled	Fire Panic	T3	Yes	115	Yes	No
Flood	Used to report a flood or high water event.	High Water Level	Water Sensor, Wired Input Module, D/W with Contact	Disabled	Yes	Yes	Yes	Disabled	Water Level	Low Level	Yes	154	No	Yes
Glass Break/Shock	Monitors any noise or vibrations coming from glass.	Intrusion, Glassbreak	Glassbreak Sensor, Shock Sensor, Wired Input Module, D/W with Contact	Disabled	Yes	Yes	No	Disabled	Intrusion	Intrusion	No	131	Yes	Yes
Heat	Used to monitor rapidly rising heat or persistent high heat condition.	Fire, heat sensor, heat rate of rise	Heat Rate of Rise, Wired Input Module Zone	Disabled	Yes	Yes	Yes	Disabled	Fire	T3	Yes	114	No	No
High Temperature	Used to monitor high temperature conditions.	High Temperature	Clare Sensor not available, Wired Input Module, D/W with Contact	Disabled	Yes	Yes	Yes	Disabled	High Temp	Low Level	Yes	158	No	Yes
Interior	A device such as an interior door that protects the interior of a protected area.	Intrusion, Interior, no delay	D/W, Wired Input Module, D/W with Contact	Disabled	No	Yes	No	Disabled	Intrusion	Intrusion	Yes	132	Yes	Yes
Interior Follower	A device such as an interior door that protects the interior of a protected area. Does not trip during entry and exit delays.	Intrusion, Interior, no delay	D/W, Wired Input Module, D/W with Contact	Disabled	No	Yes	No	Enabled	Intrusion	Intrusion	Yes	132	Yes	Yes

Profile Name	Example	Description	Applicable Sensors/Zones	Entry/Exit Delay	Active in Arm Stay	Active in Arm Away	Active in Disarm	Follower	Alarm Type	Siren Type	Require Restoral Event	Report Code	Tamper Alarm Active	Delay Alarm Report
Low Temperature	Used to monitor low temperature condctions.	Low Temperature	Clare Sensor not avialble, Wired Input Module, D/W with Contact	Disabled	Yes	Yes	Yes	Disabled	Low Temp	Low Level	Yes	159	No	Yes
Motion (Interior)	Interior motion device. Trips during an entry or exit delay.	Intrusion, Interior Motion, no delay, no restoral,	Motion, Wired Input Module, D/W with Contact	Disabled	No	Yes	No	Disabled	Intrusion	Intrusion	No	132	Yes	Yes
Motion Follower (Interior)	Interior motion device. Does not trip during an entry or exit delay.	Intrusion, Interior Motion, no delay, no restoral,	Motion, Wired Input Module, D/W with Contact	Enabled	No	Yes	No	Enabled	Intrusion	Intrusion	No	132	Yes	Yes
Motion Outdoor	Exterior motion device. Trips during an entry or exit delay.	Intrusion, Motion, Double Long delay, No restoral	Clare Sensor not avialble, Wired Input Module, D/W with Contact	Double Long	No	Yes	No	Disabled	Intrusion	Intrusion	No	136	Yes	Yes
Outdoor	Used for exterior or perimeter entry points such as an courtyard gate. Sounds siren only when tripped does not report alarm.	Intrusion, Perimeter, Double Long delay, No restoral	Gate Sensor, Wired Input Module, D/W with Contact	Double Long	No	Yes	No	Disabled	Intrusion	Intrusion	Yes	136	Yes	Yes
Outdoor - Siren Only	Used for exterior or perimeter entry points such as an courtyard gate. Sounds siren only when tripped does not report alarm.	Outdoor No Dispatch	Gate Sensor, Motion Outdoor, Wired Input Module, D/W with Contact	Double Long	No	Yes	No	Disabled	Intrusion	Intrusion	No	000	No	Yes
Panic	Panic device used to notify police of a situation and sound the siren.	Panic, Police	Keyfob, Panic Sensor, Wired Input Module, D/W with Contact	Disabled	Yes	Yes	Yes	Disabled	Panic	Intrusion	Yes	123	Yes	Yes
Panic - Siren Only	Panic device does not notify police, does sound sound the siren.	Panic, No dispatch, siren only	Keyfob, Panic Sensor, Wired Input Module, D/W with Contact	Disabled	Yes	Yes	Yes	Disabled	Panic	Intrusion	No	000	Yes	Yes
Panic Silent	Panic device used to notify police of a situation, does not sound the siren.	Panic, Police, Silent	Keyfob, Panic Sensor, Wired Input Module, D/W with Contact	Disabled	Yes	Yes	Yes	Disabled	Panic Silent	None	No	122	Yes	Yes
Perimeter	Perimeter device, used for perimeter doors, windows or gates. Entry/Exit delays do not apply, trips an immediate alarm and siren.	Intrusion, Perimeter	D/W, Wired Input Module, D/W with Contact	Disabled	Yes	Yes	No	Disabled	Intrusion	Intrusion	Yes	131	Yes	Yes
Trigger	Used on a device to trigger events and/or notifications. Does not report an alarm or sound siren.	Trigger for scenes	Any zone type for automation and notifications	Disabled	No	No	No	Disabled	None	None	No	000	No	No